ZEROTECH

INSTRUCTION MANUAL


ZEROTECH RED DOT OPTICS

TRACE TRRD125

WARNING

KEEP BATTERIES OUT OF REACH OF CHILDREN





THIS PRODUCT CONTAINS A COIN BATTERY.

THE BATTERY CAN CAUSE SEVERE OR FATAL INJURIES IN 2 HOURS OR LESS IF IT IS SWALLOWED OR PLACED INSIDE ANY PART OF THE BODY.

CONTENTS

PAGES

4 INTRODUCTION
5 LIFETIME WARRANTY
6 TRACE RED DOT OPTIC FEATURES
7 BATTERY INSTALLATION
8 BUTTON FUNCTIONS
9 WINDAGE AND ELEVATION ADJUSTMENTS
10 MOUNTING YOUR TRACE RED DOT OPTIC
11 PROPER CARE OF YOUR THRIVE RED DOT OPTIC
12 WARRANTY & CONTACT INFORMATION

WELCOME TO THE ZEROTECH FAMILY!

Customer First - We listened to you and came up with a family of optics that will satisfy the needs of our most discerning and experienced customers.

Backed by Experience - ZeroTech enjoys 60 years of experience in the Optics Market supplying high quality brands to retailers throughout Australia and the Asia Pacific.

Built for the Australian Shooter - Designed and built to endure the harsh conditions of the Australian bush and the exacting demands of the precision shooter.

Lifetime Warranty - Be safe in the knowledge that your scope is backed by our Triple A Lifetime Warranty: **'ANY OWNER, ANY PROBLEM, ALWAYS COVERED'**

LIFETIME WARRANTY

BACKED FOR LIFE!

Be safe in the knowledge that your scope is backed by our **Triple A Lifetime Warranty*:**

- Fully transferable, covers accidental damage as well as defects in materials and workmanship.
- No receipt or warranty card is required.
- We will repair or replace product with equal or similar value and/or specifications.
- We will return product to you at no charge.

*ZT AAA warranty does not cover any intentional loss or damage to ZeroTech products.



'ANY OWNER, ANY PROBLEM, ALWAYS COVERED'

TRACE TRRD125 RED DOT OPTIC FEATURES



BATTERY INSTALLATION - INSERT CR2032

1. Use the included multi tool to remove the battery cover. using the plastic battery cover tool provided.
2. Remove the CR2032 battery and discard the plastic insulator.
3. Reinstall the battery and tighten the battery cover with the multi tool until the battery cover is flush with the sight body.



NOTE: Remove and discard the plastic insulator from the battery before inserting

WARNING – KEEP BATTERIES (whether the battery is new or used) OUT OF REACH OF CHILDREN

Zerotech rifle scopes and optics with a reticle illumination feature contain coin batteries. Products containing coin batteries must be kept out of reach of children. The battery can cause severe or fatal injuries in 2 hours or less if it is swallowed or placed inside any part of the body. If you suspect your child has swallowed or inserted a button battery immediately call the **24-hour Poisons Information Centre on 13 11 26 (Australia)** for fast, expert advice.



BUTTON FUNCTIONS

1. Power on the sight by briefly pressing the + or – button.
2. Adjust the brightness intensity with using the + or – buttons.
3. If the sight is left without movement for approximately 3 ½ minutes, the sight will enter sleep mode
4. When in sleep mode, the sight will automatically switch on as soon as even the slightest movement is detected.
5. Press and hold either the + or – button for approximately three (3) seconds to power down the sight. You will need to briefly press either button to power the sight back on. The sight will resume the previous brightness setting.
6. It is recommended to power down the sight by pressing and holding the + or – buttons for short term storage.

WINDAGE AND ELEVATION ADJUSTMENTS

Each ‘click’ on the windage or elevation turret will adjust the point of impact by 0.5 MOA = 1/2” at 100y



MOUNTING YOUR TRACE RED DOT OPTIC TO YOUR FIREARM

The Trace TRRD125 red dot sight is designed to be compatible with most Weaver and Picatinny style bases and/ or rails.

Use the included T10 Torx driver on the multi tool to loosen the mount interface cross bolt several revolutions or until the mount interface can easily slip over the Picatinny or Weaver base on your firearm. Please note, the mount interface cross bolt needs to engage the slot on the base.

Once the mount interface has made proper engagement with the base, use slight forward pressure to push the sight forward towards the muzzle of your firearm. Maintain forward pressure whilst tightening the cross bolt with the T10 driver. Ensure the cross bolt is torqued to 20 in lbs (approx. 2.3 Nm).

Check to ensure the interface cross bolt remains tight after use. Apply non-permanent thread locking compound of necessary

PROPER CARE OF YOUR TRACE RED DOT OPTIC

- **ALWAYS** wipe fingerprints from the lenses using only the Zerotech lens cloth provided. Do not use other materials to wipe the lenses as this may result in damage to the lens coatings. If debris is present on the lenses, use a lens brush to remove the debris before wiping with a lens cloth.
- **ALWAYS** check the mount interface is tight after each shooting session.
- **AVOID** solvents and cleaner sprays coming into contact with your sight. If you accidentally spray solvent or cleaner onto your sight, wipe off immediately.

AVOID storing your sight for long periods with the battery installed. Always remove the battery for long term storage. Ensure the battery is stored responsibly and out of reach of children. Refer to battery warning information.

WARRANTY & CONTACT INFORMATION

Company details;

ZEROTECH INTERNATIONAL PTY LTD

For all enquiries:

AUSTRALIA / INTERNATIONAL

Ph: +612 9938 3244
Email: sales@zerotech.com.au
Web: zerotech.com.au/warranty
Address:
PO BOX 7200,
Warringah Mall
NSW, 2100, AUSTRALIA

USA

Ph: 615-674-4755
Email: sales@zerotechoptics.com
Web: zerotechoptics.com/warranty

SEE OUR RANGE OF RIFLESCOPES!

Visit our websites to see the full range of riflescopes:

THRIVE

THRIVE HD

TRACE

TRACE ADV



Australia: zerotech.com.au/riflescopes

USA: zerotechoptics.com/riflescopes

NOTES



zerotech.com.au / zerotechoptics.com



LIFETIME WARRANTY

‘ANY OWNER, ANY PROBLEM, ALWAYS COVERED’

zerotech.com.au / zerotechoptics.com